この接続の仕方は、アクセスポイント(AP)モードを使ったWiFi接続 と呼ばれます。

具体的には、データロガーがWiFiのアクセスポイントとして機能し、パソコンやスマートフォンなどの端末をそのアクセスポイントに接 続することで、設定やデータの確認などを行います 手順を簡単に説明すると、 1.データロガーのアクセスポイントに接続する。 2.WebブラウザでデータロガーのIPアドレスにアクセスする。

3.データロガーの設定画面で、接続先のWiFiネットワーク(ルーターなど)を設定する。

- 1. 無線ネットワークを開きます。
- 2. ロガーネットワーク(ネットワーク名: AP+SN)を選択して接続します。パスワードはロガーのラベルに記載されており、PWDの後ろにある文字です。



3. ブラウザを開き、「10.10.100.254」と入力します。ユーザー名とパスワードはどちらも adminです。 (推奨ブラウザ:IE 8以降、Chrome 15以降、Firefox 10以降)

| ログイン | |
|--|--|
| http://10.10.100.254 にはユーザー名と パスワードが必要です。 このサイトへの 接続は保護されていません | |
| ユーザー名 admin | |
| パスワード admin | |
| ログイン | |
| キャンセル | |

iPhoneの場合





4. ロガーの設定ページに移動します。 基本的な情報がここにリストされています。

| | | | 中文 Englis |
|-----------|----------------------------------|----------|--|
| | | | Help |
| Status | - Inverter information | | |
| Wizard | Inverter serial number T62090090 | 02320063 | The device can be used as |
| Quick Set | Firmware version (main) | | mode) to facilitate users to |
| Advanced | Firmware version (slave) | | configure the device, or it |
| Upgrade | Inverter model | | wireless information terminal |
| Restart | Rated power | VV | (STA mode) to connect the remote server via wireless |
| Reset | Current power | W | router. |
| 116361 | Yield today | 0.0 kWh | Status of remote server |
| | Total yield | 0.0 kWh | Not connected: |
| | Alerts | | last time. |
| | Last updated | 2 | If under such status, please |
| | + Device information | | (1) check the device information to see whether IP address is obtained or |
| | + Remote server information | | not; (2) check if the router is connected to internet or not; (3) check if a firewall is set on the router or not; |

5. セットアップガイドに移動し、[更新]をクリックして無線ネットワークを検索します。 ターゲットネットワークを選択して接続します。

| Status Wizard Quick Set Advanced | Please select your current | wireless network: | | | | |
|---|--|-------------------|---------|----|---|--|
| Wizard Quick Set Advanced | O IE-2.4G-TEST | | | | | 250 J 10 10 10 10 1 |
| Quick Set Advanced | () 12-2.40-1201 | 54-17-2-70-00-12 | 82 | 4 | | The setup wizard will ass you to complete the devia |
| Advanced | 0 | 0-BE-D5-20-B8-20 | 2 80 | 1 | 2 | setting within one minute |
| Auvanceu | O AP 1753738492 | 30:EA:E7:36:B:36 | 78 | 2 | 1 | |
| | O IGEN office 2.4G | 0:BE:D5:20:B8:2/ | 1 76 | 1 | 1 | |
| Ipgrade | O IGENTEST | E8:65:D4:F2:15:E | 8 74 | 6 | | |
| Pestart | ŏ | 90:5D:7C:97:95:2 | 9 74 | 1 | | |
| Cotart | O IGEN_office_2.4G | 90:5D:7C:97:95:2 | 7 72 | 1 | | |
| Reset | 0 | 90:5D:7C:97:C9:E | E5 72 | 1 | | |
| | O AP_1719065936 | 30:EA:E7:36:CF:E | 32 70 | 1 | 3 | |
| | O IGEN_office_2.4G | 90:5D:7C:97:C9:E | E3 70 | 1 | | |
| | ○ TEST+""?=,; | 4A:E:EC:9E:C3:3 | E 70 | 11 | | |
| | O IGEN_office_2.4G | 0:BE:D5:20:B7:EF | E 66 | 11 | | |
| | | | rxGII G | | - | |
| | | | | | | |
| | Add wireless network man | nually: | | | | |
| | Add wireless network man Network name (SSID) (Note: case sensitive) | IE-2.4G-TEST | | | | |
| | Add wireless network mar Network name (SSID) (Note: case sensitive) Encryption method | IE-2.4G-TEST | | | | |



6. パスワードを入力し、[次へ]をクリックします。

| | | Help |
|-----------|---|--|
| Status | Please fill in the following information: | Most systems support the |
| Wizard | | function of DHCP to obtain |
| Quick Set | Password (8-64 bytes) | IP address automatically. Please select disable and |
| Advanced | (Note: case sensitive) | add it manually if your route |
| Opgrade | | function. |
| Restart | Obtain an IP address Enable ~ | |
| Reset | IP address | |
| | Subnet mask | |
| | Gateway address | |
| | DNS server address | |
| | Back | |
| | 1 2 3 4 | |
| | | |

7. セキュリティを強化するために、以下のオプションを選択し、[次へ]をクリックします。
 (選択しなくても問題ございません)

| | | Help |
|-----------|--|--|
| Status | Enhance Security | Observe the second law |
| Wizard | | mode for AP |
| Quick Set | following methods | If you set password for the |
| Advanced | Hide AP | enter the password to |
| Upgrade | Channe the exercision mode for AP | connect to AP. |
| Restart | | Change the user name |
| Reset | Change the user name and password for Web server | server |
| | | and password for the web server, you will need to enter the new username and password to get access to the setting page. |
| | Back Next | |
| | | |



8. 設定が成功すると、次のページがポップアップ表示されます。[OK]をクリックしてモジュールを再 起動します。

| | | Help |
|-----------|---|---|
| Status | Setting complete! | |
| Wizard | | After clicking OK, the system will restart |
| Quick Set | | immediately. |
| Advanced | | |
| Upgrade | | |
| Restart | Click OK, the settings will take effect and the system will restart immediately. | |
| Reset | If you leave this interface without clicking OK, the settings will be ineffective. | |
| | | |
| | | |

9. [10.10.100.254]に再度ログインし、ここでシステム情報を確認します。 ネットワーク設定が完了すると、無線ネットワークSTAモードが有効になります。 ルーターの情報がページに表示され、リモートサーバーAに接続できます。

| Status | - Inverter information | | Help |
|-----------|---|---------------------|---|
| Wizard | Inverter and number | | The device can be used as |
| Quick Set | Firmware version (main) | | a wireless access point (Al |
| Advanced | Firmware version (slave) | | configure the device, or it |
| Advanced | Inverter model | | can also be used as a wireless information termin |
| Upgrade | Rated power | W | (STA mode) to connect th |
| Restart | Current power | W | remote server via wireless router. |
| Reset | Yield today | kWh | |
| | Total yield | kWh | Status of remote server Not connected: Connectid |
| | Alerts | | to server failed last time. |
| | Last updated | 1422 | check the issues as follows |
| | Device information Device serial number | 1704013242 | IP address is obtained or not; (2) check if the router is |
| | Firmware version | LSW3_14_FFFF_1.0.23 | connected to internet or no |
| | Wireless AP mode | Disable | (3) check if a firewall is set on the router or not- |
| | SSID | | on one router or more |
| | IP address | | Connected: Connection to server successful last time |
| | MAC address | | |
| | Wireless STA mode | Enable | Unknown: No connection to server.Please check |
| | Router SSID | IE-2.4G-TEST | again in 5 minutes. |
| | Signal Quality | 100% | |
| | IP address | 172.16.30.247 | |
| | MAC address | 98:D8:63:71:8D:B0 | |
| | - Remote server information | | |
| | Remote server A | Connected | |
| | Remote server B | Not connected | |



Web Ver:1.0.24